

Compax 3 – CMS & CMM

Electrical Information

MODEL NO. CMS/M_ _ _	210	230	260	300	350	400	450	
208/1/60								
RLA	-	-	-	-	-	-	-	
MCA	-	-	-	-	-	-	-	
MOP	-	-	-	-	-	-	-	
208/3/60								
RLA	50.1	59.1	60.3	66.6	96.2	102.5	111.5	
MCA	56.3	66.4	67.8	74.9	108.2	115.3	125.4	
MOP	80.0	90.0	90.0	100.0	150.0	150.0	175.0	
460/3/60								
RLA	24.4	29.4	33.4	35.9	37.2	46.1	53.8	
MCA	27.5	33.1	37.6	40.4	41.8	51.9	60.6	
MOP	35.0	45.0	50.0	50.0	60.0	70.0	80.0	
575/3/60								
RLA	17.9	24.4	24.4	25.7	29.4	39.7	47.4	
MCA	20.2	27.5	27.5	28.9	33.1	44.6	53.3	
MOP	25.0	35.0	35.0	40.0	45.0	60.0	70.0	
Series	Compax Size 3							
Compressor	Type	Scroll	Scroll	Scroll	Scroll	Scroll	Scroll	Scroll
Compressor	Quantity	2	2	2	2	2	2	2

